Quantum Speedup for Index Modulation

Naoki Ishikawa, *Member, IEEE*.

Abstract—This paper presents a quantum-assisted index modulation for next-generation IoT wireless networks. The NP-hard index selection problem is first formulated by a quadratic unconstrained binary optimization (QUBO) problem consisting of constraints of feasible solutions. To minimize the number of qubits required for a quantum circuit, this formulation is then simplified by a dictionary-based approach that partially exploits a classical computer. For both formulations, the numbers of required qubits and non-zero elements in QUBO matrices are analyzed algebraically, and found to be in close agreement with the actual measurement. It is observed that the Grover adaptive search can provide the quantum speedup for the index selection problem. This promising result implies that the on-off structure of index modulation is suitable for quantum computation, and future fault-tolerant quantum computers may be useful for obtaining high-performance index activation patterns.

Index Terms—Optimization, quadratic unconstrained binary optimization (QUBO), quantum computing, quantum speedup, Grover search, multiple-input multiple-output (MIMO), orthogonal frequency-division multiplexing (OFDM), index modulation, internet of things (IoT).

I. INTRODUCTION

INDEX modulation (IM) represents information by switching elements on and off. Since Mesleh *et al.* proposed IM for multiple-input multiple-output (MIMO) scenarios [1], a tremendous number of papers have been published trying to break the trade-off between performance and computational complexity, especially in the field of wireless communications. The sparse structure of IM helps to reduce the number of multiplications. In particular, it has been demonstrated that significant gains can be achieved at low transmission rates, and it is expected to play an important role in IoT wireless networks [2]. Although this fact is not well-known, the first pioneering concept was established by Slepian in 1965 [3]. Beyond the communications field, applications similar to IM have been proposed in the fields of data storage and information hiding [4].

IM requires combinatorial optimization to determine which indices should be used. Specifically, any K number of elements are selected from among M elements such as transmit antennas or subcarriers. The corresponding number of patterns is $\binom{M}{K}$, which must be rounded down to a power of two, Q , to convey binary information. This optimization problem is NP-hard, and in this paper we refer to it as the *index selection problem*, which leads to a combinatorial explosion.

Initially, the most common method was to use the first Q rows of the combinatorial matrix defined in [5]. The challenge with this method is that the selection probability of each element is unbalanced. To mitigate this unbalanced selection, Wen *et al.* proposed an efficient solution based on the greedy algorithm [6]. Although the computational complexity of [6] is negligible, the achievable minimum Hamming distance is two in any case, which limits its performance. In [7], Dang *et al.* proposed a lexicographic design method for IM. The design method of [7] requires periodic feedback of channel state information in order to activate subcarriers that have high channel gains. Inspired by [7], a genetic algorithm-aided method was proposed in [8, 9], although metaheuristics are difficult to guarantee optimality. It has been pointed out that the index selection problem is related to error-correcting codes [10–12]. Specifically, Fazeli and Nguyen used error-correcting codes designed for a Z-channel as activation patterns [10]. But, an error-correcting code aims at maximizing the minimum Hamming distance and does allow unbalanced activation of elements. In [8], the index selection problem is formulated as an integer linear programming problem, which can activate each element with an equal probability. However, it cannot be solved on a classical computer depending on the size of the search space.

Feynman invented computation by a reversible machine composed of unitary gates in 1986 [13]. He pointed out that the minimum energy required by a reversible machine is independent of the complexity of the calculation. Thus, a reversible quantum computer can be characterized by its power-saving performance. Quantum computers have advantages over classical computers in two major aspects: Shor's algorithm [14] for integer factoring in polynomial time and Grover search [15] that can provide the quantum speedup. Noise in quantum circuits is a critical problem, and quantum error-correcting codes have been intensively researched [16, 17] to implement fault-tolerant, large-scale quantum computers. There are still many challenges for industrial applications due to the non-negligible noise. For example, in the case of Shor's algorithm implemented in a real quantum computer, it could factor $21 = 3 \cdot 7$, but it failed to factor $35 = 5 \cdot 7$ [18].

Grover search [15] can find a specific element from a database of unsorted N elements with query complexity $O(\sqrt{N})$. This surprising property is called quadratic speedup, or quantum speedup. Similarly, in the case of the minimum value search, the query complexity is of the order of $O(\sqrt{N})$ [19]. The Grover search can be extended to solve minimization problems. This extended counterpart is termed *Grover adaptive search* (GAS) [20], and it can also provide the quantum speedup. The conventional GAS requires a complex quantum circuit to evaluate an objective function. In [21, 22], Gilliam *et al.* solved this open issue by using a quantum dictionary

N. Ishikawa is with the Faculty of Engineering, Yokohama National University, 240-8501 Kanagawa, Japan (e-mail: ishikawa-naoki-fr@ynu.ac.jp).

©2021 IEEE. Personal use of this material is permitted. Permission from IEEE must be obtained for all other uses, in any current or future media, including reprinting/republishing this material for advertising or promotional purposes, creating new collective works, for resale or redistribution to servers or lists, or reuse of any copyrighted component of this work in other works. DOI: <https://doi.org/10.1109/ACCESS.2021.3103207>

to store key-value pairs in entangled quantum registers, which allows for the representation of a quadratic polynomial function.¹ The quantum circuit for GAS requires qubits to encode an objective function, in addition to qubits for binary variables. It is shown in [22] that portfolio optimization, which is a quadratic unconstrained binary optimization (QUBO) problem, can be solved on a real quantum computer.

The variational quantum eigensolver [24] and the quantum approximate optimization algorithm (QAOA) [25] are well-known methods for solving a QUBO problem with a reversible quantum computer [26]. Other approaches, quantum annealing [27, 28] and coherent Ising machine [29–31], are useful in industrial applications as both can operate with low latency, although the theoretical speedup has not been proven. Hence, this paper deals only with GAS that can provide the quantum speedup.

In [32], Botsinis *et al.* demonstrated the potential of quantum search algorithms to alleviate the complexity involved in maximum likelihood (ML) detection, which is the first attempt in the literature. Specifically, Botsinis *et al.* used the Boyer-Brassard-Høyer-Tapp [33] and the Dürr-Høyer search algorithms [19] for performing ML detection of discrete symbols on a quantum computer [34]. Besides, Matsumine *et al.* used QAOA for performing quasi-ML decoding of linear error-correcting codes [35]. For more information on quantum optimization in wireless communications, a comprehensive survey can be found in [36].

Against this background, the NP-hard index selection problem is newly solved by GAS that can provide the quantum speedup. The on-off structure of IM is compatible with quantum computation, which has not been pointed out in any literature to the best of the author's knowledge. The major contributions of this paper are organized as follows:

- 1) It is verified for the first time that the index selection problem can be solved by a quantum computer. A constraint-based formulation is conceived for the index selection problem. Then, a dictionary-based formulation is conceived to reduce the number of required qubits. This dictionary-based formulation defines the problem using good candidates that maximize the minimum Hamming distance, which is partially done by a classical computer.
- 2) The number of qubits and the number of non-zero elements in the QUBO matrix are analyzed for both formulations. This analysis is important to estimate the feasibility of the quantum circuit. Conventional research on quantum algorithms assumes the existence of an ideal quantum oracle that can evaluate the objective function, making it difficult to discuss in detail the number of qubits and the depth of a quantum circuit.
- 3) Numerical analysis demonstrates a reduction in the average number of trials compared to the classic exhaustive search, confirming the quantum speedup as expected in theory, where a noisy quantum circuit is considered.

¹Note that the first paper was published on arXiv on December 9, 2019 [23].

TABLE I
LIST OF IMPORTANT MATHEMATICAL SYMBOLS

$\mathbb{B}$		Binary numbers
$\mathbb{R}$		Real numbers
$\mathbb{C}$		Complex numbers
$\mathbb{Z}$		Integers
M	$\in \mathbb{Z}$	Number of transmit antennas or subcarriers
K	$\in \mathbb{Z}$	Number of activated elements
Q	$\in \mathbb{Z}$	Number of activation patterns
L	$\in \mathbb{Z}$	Constellation size
B	$\in \mathbb{Z}$	Bitwidth [bit]
R	$\in \mathbb{R}$	Transmission rate [bps/Hz]
H'	$\in \mathbb{Z}$	Threshold for minimum Hamming distance
Q'	$\in \mathbb{Z}$	Number of rows in $\mathbf{C}^{(H')}$
$E(\cdot)$	$\in \mathbb{Z}$	An objective function
$E_1(\cdot)$	$\in \mathbb{Z}$	Constraint-based objective function
$E_2(\cdot)$	$\in \mathbb{Z}$	Dictionary-based objective function
k	$\in \mathbb{Z}$	QUBO coefficient
x	$\in \mathbb{B}$	QUBO variable
y	$\in \mathbb{Z}$	An integer that is adaptively changed by GAS
n	$\in \mathbb{Z}$	Number of QUBO variables in $E(\cdot)$
m	$\in \mathbb{Z}$	Number of qubits required to encode $E(\cdot)$
n_1	$\in \mathbb{Z}$	Number of QUBO variables in $E_1(\cdot)$
m_1	$\in \mathbb{Z}$	Number of qubits required to encode $E_1(\cdot)$
n_2	$\in \mathbb{Z}$	Number of QUBO variables in $E_2(\cdot)$
m_2	$\in \mathbb{Z}$	Number of qubits required to encode $E_2(\cdot)$
$\mathbf{C}(M, K)$	$\in \mathbb{B}^{\binom{M}{K} \times M}$	Combinatorial matrix [5]
$\mathbf{C}^{(H')}$	$\in \mathbb{Z}^{Q' \times M}$	Submatrix of $\mathbf{C}(M, K)$
$\mathbf{c}_i$	$\in \mathbb{B}^M$	The i -th row of $\mathbf{C}(M, K) = \mathbf{C}^{(2)}$

The remainder of this paper is organized as follows. Section II introduces GAS, while Section III introduces IM. Section IV proposes two QUBO formulations for the index selection problem, and Section V compares these two formulations. Finally, Section VI concludes this paper.

Italicized symbols represent scalar values; bold symbols represent vectors and matrices. Table I summarizes a list of important mathematical symbols used in this paper.

II. GROVER ADAPTIVE SEARCH

Grover Adaptive Search (GAS) [20] is an extension of the well-known Grover search [15] that can solve a QUBO problem with query complexity $O(\sqrt{N})$. Gilliam *et al.* proposed an efficient method to construct a quantum circuit that can directly evaluate a quadratic polynomial function [22], which is an objective function of the QUBO problem. Specifically, the quantum dictionary [37] is used to encode a quadratic polynomial $E(\mathbf{x}) \in \mathbb{Z}$, and it is represented by a quantum circuit composed of phase shift gates. For a given integer $y \in \mathbb{Z}$, the circuit labels quantum states where $E(\mathbf{x}) - y$ is negative, and it finds the global optimal solution by adaptively varying y through multiple trials. Here, the number of queries to the quantum circuit is ideally $\left\lceil \frac{\pi}{4} \sqrt{N} \right\rceil = O(\sqrt{N})$ when we have n variables in the QUBO problem and $N = 2^n$. Because it is less than $O(N)$ in the case of exhaustive search, this phenomenon is called quadratic speedup or quantum speedup.²

²If there are more than $s \geq 2$ optimal solutions, the query complexity will be $\left\lceil \frac{\pi}{4} \sqrt{\frac{N}{s}} \right\rceil$ [22]. Additionally, the specific time complexity of quantum algorithms is not yet clear, as it depends on the quantum hardware.

For n binary variables $\mathbf{x} = [x_1, \dots, x_n] \in \mathbb{B}^n$, a QUBO problem is defined by

$$\tilde{\mathbf{x}} = \arg \min_{\mathbf{x}} E(\mathbf{x}) = \arg \min_{\mathbf{x}} \mathbf{x}^T \mathbf{M} \mathbf{x}, \quad (1)$$

and $\mathbf{M}$ is called a QUBO matrix, that represents coefficients. Note that $x_1^2 = x_1, \dots, x_n^2 = x_n$ are valid because each variable is binary. A QUBO problem is known as an NP-hard problem [38], and requires complex combinatorial optimization relying on the branch and bound.

The quantum circuit for GAS requires $n + m$ qubits [22], where n is the number of binary variables in the QUBO problem, and m is used to encode the objective function. Let k be a coefficient of the objective function, which is an element of the QUBO matrix $\mathbf{M}$, and m is the smallest integer that satisfies the following conditions:

$$\begin{cases} -2^{m-1} \leq k < 2^{m-1} \\ -2^{m-1} \leq \min[E(\mathbf{x})] \leq \max[E(\mathbf{x})] < 2^{m-1} \end{cases} \quad (2)$$

A coefficient k is represented by the phase of the following unitary operator $\mathbf{U}_G(\theta)$ and $\theta = 2\pi k/2^m$ [22].

$$\mathbf{U}_G(\theta) = \mathbf{R}(2^0\theta) \otimes \mathbf{R}(2^1\theta) \otimes \dots \otimes \mathbf{R}(2^{m-1}\theta) \in \mathbb{C}^{2^m \times 2^m} \quad (3)$$

Here, $\mathbf{R}(\cdot) \in \mathbb{C}^{2 \times 2}$ denotes the phase shift gate and $\otimes$ denotes the tensor product. The quantum circuit for GAS becomes most efficient when the coefficients of the objective function are limited to integers. It is possible to represent real numbers if we use $\mathbf{U}_{\text{Fejér}}(\theta)$ defined in [22], instead of $\mathbf{U}_G(\theta)$. Finally, the interaction between the unitary operator and the n qubits enables the encoding of the objective function.

Let us check a specific example. This example is a special case of the proposed constraint-based formulation, which will be described in Section IV-A. For $n = 4$ QUBO variables $\mathbf{x} = [x_1 \ x_2 \ x_3 \ x_4] \in \mathbb{B}^4$, an example formulation is given by

$$\begin{aligned} \min_{\mathbf{x}} \quad & E_1(\mathbf{x}) \\ \text{s.t.} \quad & x_i \in \{0, 1\} \quad (i = 1, \dots, 4) \end{aligned} \quad (4)$$

where the objective function is defined by

$$\begin{aligned} E_1(\mathbf{x}) &= (x_1 + x_2 - 1)^2 + (x_3 + x_4 - 1)^2 + \\ &\quad (x_1 + x_3 - 1)^2 + (x_2 + x_4 - 1)^2 \\ &= -2x_1 - 2x_2 - 2x_3 - 2x_4 \\ &\quad + 2x_1x_2 + 2x_1x_3 + 2x_2x_4 + 2x_3x_4 + 4 \\ &= \mathbf{x}^T \mathbf{M} \mathbf{x} + 4 \end{aligned} \quad (5)$$

and the QUBO matrix is calculated as

$$\mathbf{M} = \begin{bmatrix} -2 & 2 & 2 & 0 \\ 0 & -2 & 0 & 2 \\ 0 & 0 & -2 & 2 \\ 0 & 0 & 0 & -2 \end{bmatrix}. \quad (6)$$

The above $E_1(\mathbf{x})$ shows that the coefficients are limited to 2 and -2. Also, the maximum of $E_1(\mathbf{x})$ is obviously 4, and the minimum is 0. Thus, from (2), the minimum integer that satisfies $-2^{m-1} \leq -2$ and $4 < 2^{m-1}$ is $m = 4$.

Fig. 1 shows a part of quantum circuit for GAS, where we have $n = 4$ qubits for QUBO variables $\mathbf{x} = [x_1 \ x_2 \ x_3 \ x_4]$

and $m = 4$ qubits $|z\rangle_4$ for encoding the objective function (5). $\mathbf{H}^{\otimes 8} \in \mathbb{C}^{2^8 \times 2^8}$ denotes the Hadamard gate that creates an equal superposition of all states. As shown in Fig. 1, the integer 4 corresponds to $\mathbf{U}_G(\pi/2)$, 2 corresponds to $\mathbf{U}_G(\pi/4)$, and -2 corresponds to $\mathbf{U}_G(-\pi/4)$. The term +4 is not connected to the $n = 4$ qubits. The term $-2x_1$ is connected to $|x_1\rangle$, while the term $+2x_1x_2$ is connected to $|x_1\rangle$ and $|x_2\rangle$. At the end, the inverse quantum Fourier transform (IQFT) decodes the result encoded by the unitary operators $\mathbf{U}_G(\theta)$.

As described above, the number of required qubits increases in proportion to $n + m$. This means that the number of variables in a QUBO problem, the value range of coefficients and objective function determines the size of quantum circuit. Furthermore, the quantum circuit contains the same number of unitary operators as the number of non-zero elements in the QUBO matrix $\mathbf{M}$, which determines the depth of quantum circuit. Therefore, the algebraic analysis of n , m , and the number of non-zero elements in the QUBO matrix is very important, which will be analyzed in detail in this paper.

III. INDEX MODULATION

Index modulation (IM) conveys information by switching elements on and off. For example, part of transmit antennas are selected in the generalized spatial modulation [39], or part of subcarriers are selected in the subcarrier IM [40]. Any K out of M elements are selected, and the information is assigned to that selection pattern. This selection pattern can be defined by the combinatorial matrix $\mathbf{C}(M, K)$ in a recursive manner as follows [5]:

$$\mathbf{C}(M, K) = \begin{bmatrix} \mathbf{1} & \mathbf{C}(M-1, K-1) \\ \mathbf{0} & \mathbf{C}(M-1, K) \end{bmatrix} \in \mathbb{B}^{\binom{M}{K} \times M}. \quad (7)$$

Here, $\binom{M}{K} = M!/K!(M-K)!$ denotes the binomial coefficient. In (7), $\mathbf{0}$ represents a zero vector of length $\binom{M-1}{K-1}$, whereas $\mathbf{1}$ represents a one vector of length $\binom{M-1}{K-1}$. When the number of columns reaches M , the recursive call is stopped. If we have $\mathbf{C}(M, K) = (4, 2)$, the combinatorial matrix is exemplified by

$$\mathbf{C}(4, 2) = \begin{bmatrix} 1 & 1 & 0 & 0 \\ 1 & 0 & 1 & 0 \\ 1 & 0 & 0 & 1 \\ 0 & 1 & 1 & 0 \\ 0 & 1 & 0 & 1 \\ 0 & 0 & 1 & 1 \end{bmatrix} \in \mathbb{B}^{6 \times 4}. \quad (8)$$

Through the selected K elements, K complex-valued symbols $s_1, \dots, s_K \in \mathbb{C}$ are transmitted, where the L -ary amplitude and phase-shift keying is used. The transmission rate is $R = B$ for generalized spatial modulation and $R = B/M$ for subcarrier IM, where the length of bits is

$$B = \left\lceil \log_2 \binom{M}{K} \right\rceil + K \log_2(L) \text{ [bit]}. \quad (9)$$

As an example, in the $(M, K) = (2, 1)$ case, the combinatorial matrix is calculated as the identity matrix of size two, i.e., $\mathbf{C}(2, 1) = \mathbf{I}_2$. Then, if we use $L = 2$ constellation, the transmit vectors are given by $[+1 \ 0]^T, [-1 \ 0]^T, [0 \ +1]^T, [0 \ -1]^T \in$

Fig. 2. The combinatorial explosion of the index selection problem, where the number of elements was increased from $M = 2$ to 16, the number of selected elements was varied from $K = 2$ to $M - 1$, and the number of selected rows was varied from $Q = 2$ to $Q_{\max}$.

IV. PROPOSED MATHEMATICAL FORMULATIONS

Since the on-off structure of IM is suitable for quantum computation, the index selection problem is formulated by a QUBO problem and is solved by the GAS [22] that can provide the quantum speedup. In general, a QUBO problem is known as an NP-hard problem [38].

In the following, two formulations are newly conceived for the index selection problem. The first is a straightforward approach that only relies on constraints of variables. It works only with a quantum computer, but requires a large number of qubits. The second is an improved counterpart that exploits the combinatorial matrix. It requires both classical and quantum computers, but requires fewer qubits. Later, both are termed *constraint-based* and *dictionary-based* formulations, respectively.

Unlike the conventional approach [8], the proposed formulations are designed so that variables are binary and the corresponding objective function is a polynomial of the second degree that only returns an integer. The conventional approach can be transformed into a QUBO-like expression as given in (12), but it is a challenging task to convert the minimum operation given in (13) to a QUBO problem.

A. Constraint-Based Formulation

In this constraint-based approach, we focus only on constraints of feasible solutions that will be obtained. The solutions are binary variables with Q rows and M columns, and have two constraints:

- 1) the sum of each row is K and
- 2) the sum of each column is J on average,

where $J = \lfloor Q \cdot K / M \rfloor$ has to be an integer. The constraint on J is required due to the structure of the quantum circuit, as

described in Section II. The constraint-based formulation can be designed by

$$\begin{aligned} \min_{\mathbf{x}} \quad & E_1(\mathbf{x}) \\ \text{s.t.} \quad & x_i \in \{0, 1\} \quad (i = 1, \dots, n_1) \end{aligned} \quad (15)$$

where the objective function is given by

$$\begin{aligned} E_1(\mathbf{x}) = & \sum_{q=1}^Q \left(\sum_{m=1}^M (x_{(q-1)M+m}) - K \right)^2 \\ & + \sum_{m=1}^M \left(\sum_{q=1}^Q (x_{(q-1)M+m}) - J \right)^2 \in \mathbb{Z}, \end{aligned} \quad (16)$$

and we have $n_1 = QM$ binary variables $\mathbf{x} = [x_1 \dots x_{QM}]^T \in \mathbb{B}^{QM \times 1}$. The maximum of $E_1(\mathbf{x})$ is derived as

$$\max(E_1(\mathbf{x})) = \begin{cases} Q(M-K)^2 + M(Q-J)^2 & (K < \frac{M}{2}) \\ QK^2 + MJ^2 & (K \geq \frac{M}{2}) \end{cases}, \quad (17)$$

and the number of qubits required to encode $E_1(\mathbf{x})$ is

$$m_1 = \lceil \log_2(\max(E_1(\mathbf{x}))) \rceil + 1. \quad (18)$$

Finally, this constraint-based formulation requires $n_1 + m_1$ qubits for the GAS circuit. According to algebraic analysis, the number of required qubits increases as

$$n_1 + m_1 = O(QM), \quad (19)$$

where $O(\cdot)$ is an asymptotic notation. The number of non-zero elements in the QUBO matrix of (16) increases as

$$\begin{aligned} QM + Q \binom{M}{2} + M \binom{Q}{2} &= \frac{QM(Q+M)}{2} \\ &= O(QM(Q+M)). \end{aligned} \quad (20)$$

As an example, for the IM parameters $(M, K, Q) = (4, 2, 4)$, we have $n_1 = QM = 16$ and $\max(E_1(\mathbf{x})) = QK^2 + MJ^2 = 16 + 16 = 32$ that results in $m_1 = 6$. Hence, the GAS circuit requires $n_1 + m_1 = 16 + 6 = 22$ qubits for the proposed constraint-based formulation. According to (16), the objective function can be calculated as

$$E_1(\mathbf{x}) = \mathbf{x}^T \mathbf{M} \mathbf{x} + 32, \quad (22)$$

where the QUBO matrix $\mathbf{M}$ is given by (21). Since this example originally has a small search space, i.e., $S(4, 2, 4) = \binom{6}{4} = 15$, it is necessary to consider a formulation with fewer qubits.

B. Dictionary-Based Formulation

It is possible to reduce the number of qubits for the GAS circuit by reducing the number of variables and also narrowing the value range of the objective function. To reduce the number of variables, we limit solutions of the index selection to good candidates rather than formulating it only with constraints. Specifically, in the same manner as [8], we construct a submatrix of the combinatorial matrix $\mathbf{C}(M, K)$ defined in (7). Based on this submatrix, we again formulate the index selection problem as a simplified QUBO problem.

$$\mathbf{M} = \begin{bmatrix} -6 & 2 & 2 & 2 & 2 & 0 & 0 & 0 & 2 & 0 & 0 & 0 & 2 & 0 & 0 & 0 \\ 0 & -6 & 2 & 2 & 0 & 2 & 0 & 0 & 0 & 2 & 0 & 0 & 2 & 0 & 0 & 0 \\ 0 & 0 & -6 & 2 & 0 & 0 & 2 & 0 & 0 & 0 & 2 & 0 & 0 & 0 & 2 & 0 \\ 0 & 0 & 0 & -6 & 0 & 0 & 0 & 2 & 0 & 0 & 0 & 2 & 0 & 0 & 0 & 2 \\ 0 & 0 & 0 & 0 & -6 & 2 & 2 & 2 & 2 & 0 & 0 & 0 & 2 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & -6 & 2 & 2 & 2 & 0 & 2 & 0 & 0 & 0 & 2 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & -6 & 2 & 0 & 0 & 2 & 0 & 0 & 0 & 2 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & -6 & 2 & 2 & 2 & 2 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & -6 & 2 & 2 & 2 & 2 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & -6 & 2 & 2 & 0 & 0 & 2 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & -6 & 2 & 0 & 0 & 2 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & -6 & 2 & 2 & 2 & 2 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & -6 & 2 & 2 & 2 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & -6 & 2 & 2 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & -6 & 2 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 & -6 \end{bmatrix} \quad (21)$$

First, we construct a submatrix of $\mathbf{C}(M, K)$ that is composed of good candidates in terms of the minimum Hamming distance. For simplicity, $\mathbf{C}(M, K)$ is denoted by $\mathbf{C}^{(2)}$ because its minimum Hamming distance between each pair of rows is $H = 2$. Later, the i -th row of $\mathbf{C}^{(2)}$ is denoted by $\mathbf{c}_i \in \mathbb{B}^M$ for $1 \leq i \leq \binom{M}{K}$. Let H be the threshold of the minimum Hamming distance, the submatrix $\mathbf{C}^{(H)}$ is defined by a set of rows that satisfy $\text{Hamming}(\mathbf{c}_i, \mathbf{c}_j) \geq H$ for $1 \leq i < j \leq \binom{M}{K}$. Here, $\text{Hamming}(\cdot, \cdot)$ denotes the Hamming distance between two binary vectors. For example, in the $(M, K) = (4, 2)$ case, $\mathbf{C}^{(4)}$ is a submatrix of $\mathbf{C}^{(2)}$ as follows:

$$\mathbf{C}^{(4)} = \begin{bmatrix} 1 & 1 & 0 & 0 \\ 0 & 0 & 1 & 1 \end{bmatrix}, \quad (23)$$

that obviously satisfies the minimum Hamming distance $H = 4$. A specific construction algorithm for $\mathbf{C}^{(H)}$ can be found in [8, Algorithm 3]. Note that the complexity imposed by this algorithm is negligible as compared to the complexity $S(M, K, Q)$ of the index selection problem.

Second, we find the minimum H' that satisfies $Q' = \text{nrow}(\mathbf{C}^{(H')}) \geq Q$ to determine which of submatrices $\{\mathbf{C}^{(2)}, \mathbf{C}^{(4)}, \mathbf{C}^{(6)}, \dots\}$ should be used. For example, for the IM parameters $(M, K, Q) = (4, 2, 2)$, we can find the threshold $H' = 4$ and use the best dictionary $\mathbf{C}^{(H'=4)}$ that has $Q' = 2$ rows.

Finally, the novel dictionary-based formulation can be designed by

$$\begin{aligned} \min_{\mathbf{x}} \quad & E_2(\mathbf{x}) \\ \text{s.t.} \quad & x_i \in \{0, 1\} \quad (i = 1, \dots, n_2) \end{aligned} \quad (24)$$

where the objective function is given by

$$E_2(\mathbf{x}) = \sum_{m=1}^M \left(\sum_{r=1}^{Q'} (c_{r,m} \cdot x_r) - J \right)^2 \in \mathbb{Z}. \quad (25)$$

In (25), we have $J = \lfloor Q \cdot K/M \rfloor$ and $n_2 = Q'$ binary variables $\mathbf{x} = [x_1 \dots x_{Q'}]^T \in \mathbb{B}^{Q' \times 1}$. Additionally, $c_{r,m}$ denotes the element at the r -th row and m -th column of the selected dictionary $\mathbf{C}^{(H')}$. The maximum of $E_2(\mathbf{x})$ is derived as

$$\max(E_2(\mathbf{x})) = \begin{cases} K^2(Q' - Q)^2/M & \left(Q < \frac{Q'}{2} \right) \\ K^2Q^2/M & \left(Q \geq \frac{Q'}{2} \right) \end{cases}, \quad (26)$$

and the number of qubits required to encode $E_2(\mathbf{x})$ is

$$m_2 = \lceil \log_2(\max(E_2(\mathbf{x}))) \rceil + 1. \quad (27)$$

Algorithm 1 Counting algorithm for the number of non-zero elements in the QUBO matrix corresponding to (25).

Input: $Q' \in \mathbb{Z}, \mathbf{c}_1, \dots, \mathbf{c}_{Q'} \in \mathbb{Z}^M$

Output: c_s

```

1:  $c_s = Q' - 1$ 
2:  $x = 2$ 
3: while  $x < Q'$  do
4:    $y = x + 1$ 
5:   while  $y \leq Q'$  do
6:     if  $\langle \mathbf{c}_x, \mathbf{c}_y \rangle \neq 0$  then
7:        $c_s = c_s + 1$ 
8:     end if
9:      $y = y + 1$ 
10:  end while
11:   $x = x + 1$ 
12: end while
13: return  $c_s$ 
```

The dictionary-based formulation can be further simplified by limiting $x_1 = 1$. Then, the required qubits is reduced from $n_2 = Q'$ to $n_2 = Q' - 1$. The addition of this constraint can be expressed only by rewriting the objective function.

According to algebraic analysis, the number of required qubits increases as

$$\begin{aligned} n_2 + m_2 &= Q' + 2 \log_2(K) + \log_2(Q) \\ &= O(Q' + \log(K) + \log(Q)). \end{aligned} \quad (28)$$

Unlike the constraint-based formulation, the number of non-zero elements in the QUBO matrix of (25) is difficult to analyze algebraically because it varies depending on the combinatorial matrix $\mathbf{C}^{(H')}$. Here, Algorithm 1 is conceived to count the number of non-zero elements, which investigates the mutual connections between variables. The number of non-zero elements is counted in a variable c_s , and the initial value is $c_s = n_2 = Q' - 1$ since we have n_2 variables. For any two rows $(\mathbf{c}_x, \mathbf{c}_y)$ of the combinatorial matrix $\mathbf{C}^{(H')}$, this algorithm calculates the inner product $\langle \mathbf{c}_x, \mathbf{c}_y \rangle$ and adds 1 to c if this inner product is not zero. Algorithm 1 can be further transformed into the following expression, and it returns a quadratic expression with respect to Q' . Thus, the number of non-zero elements in the dictionary-based QUBO matrix is $O(Q'^2)$.

$$Q' - 1 + \sum_{x=2}^{Q'-1} \sum_{y=x+1}^{Q'} \min(1, \langle \mathbf{c}_x, \mathbf{c}_y \rangle) = O(Q'^2) \quad (29)$$

Let us check a specific example. In the $(M, K, Q) = (4, 2, 4)$ case, we can find the threshold for the minimum Hamming distance $H' = 2$ and use the dictionary $\mathbf{C}^{(H'=2)}$ defined in (8). The corresponding objective function is

$$\begin{aligned} E_2(\mathbf{x}) &= \sum_{m=1}^4 \left(\sum_{r=1}^6 (c_{r,m} \cdot x_r) - 2 \right)^2 \\ &= (x_1 + x_2 + x_3 - 2)^2 + (x_1 + x_4 + x_5 - 2)^2 \\ &\quad + (x_2 + x_4 + x_6 - 2)^2 + (x_3 + x_5 + x_6 - 2)^2. \end{aligned} \quad (30)$$

Then, the optimal solution would be $E_2([1 \ 1 \ 0 \ 0 \ 1 \ 1]^T) = 0$ that indicates it is better to use the first, second, fifth, and sixth rows of $\mathbf{C}^{(2)}$.

For the simplified case that has $n_2 = Q' - 1 = 5$, the number of required qubits is calculated as $n_2 + m_2 = 10$, which is about half of that of the constraint-based formulation. We can limit $x_1 = 1$ and rewrite the objective function for $\mathbf{x}' = [x_2 \ x_3 \ x_4 \ x_5 \ x_6]^T \in \mathbb{B}^{5 \times 1}$ as⁴

$$\begin{aligned} E_2(\mathbf{x}') &= (x_2 + x_3 - 1)^2 + (x_4 + x_5 - 1)^2 \\ &\quad + (x_2 + x_4 + x_6 - 2)^2 + (x_3 + x_5 + x_6 - 2)^2 \\ &= -4x_2^2 + 2x_2x_3 + 2x_2x_4 + 2x_2x_6 - 4x_3^2 + 2x_3x_5 \\ &\quad + 2x_3x_6 - 4x_4^2 + 2x_4x_5 + 2x_4x_6 - 4x_5^2 \\ &\quad + 2x_5x_6 - 6x_6^2 + 10 = \mathbf{x}'^T \mathbf{M} \mathbf{x}' + 10, \end{aligned} \quad (31)$$

where we have the QUBO matrix of

$$\mathbf{M} = \begin{bmatrix} -4 & 2 & 2 & 0 & 2 \\ 0 & -4 & 0 & 2 & 2 \\ 0 & 0 & -4 & 2 & 2 \\ 0 & 0 & 0 & -4 & 2 \\ 0 & 0 & 0 & 0 & -6 \end{bmatrix}. \quad (32)$$

We obtain the optimal solution $E_2([1 \ 0 \ 0 \ 1 \ 1]^T) = 0$, that indicates the second, fifth, and sixth rows should be used, in addition to the first row of (8). The number of non-zero elements in the QUBO matrix of (32) is 13, which is much smaller than that of the constraint-based formulation (21), 64.

V. NUMERICAL ANALYSIS

In this section, both constraint-based and dictionary-based formulations are compared in terms of the complexity of quantum circuit. Then, the optimization process of GAS is exemplified by simulations only for the dictionary-based formulation, which is suitable for visualization of the optimization process because of the small number of qubits required. Finally, the obtained activation patterns are compared with the conventional methods in terms of bit error ratio (BER) and average mutual information (AMI).

IBM Qiskit [41] and its noisy quantum circuit simulator backend were used in the simulations. In the performance comparisons, the idealistic OFDM channel [2] was assumed, and the maximum likelihood detector was used for all the considered methods.

(a) The number of qubits.

(b) The number of non-zero elements in $\mathbf{M}$.

Fig. 3. Comparisons between the constraint-based and dictionary-based formulations, where the IM parameters were the same as those used in Fig. 2.

A. Constraint- vs. dictionary-based formulations

First, in Fig. 3, the proposed constraint-based and dictionary-based formulations were compared in terms of the number of required qubits and the number of non-zero elements in the QUBO matrix, $\mathbf{M}$. The horizontal axis of Fig. 3 corresponds to the index of IM parameters that were exactly the same as those used in Fig. 2. As shown in Fig. 3(a), the dictionary-based formulation succeeded in reducing the number of required qubits compared to the constraint-based formulation without any exception. Specifically, the dictionary-based formulation reduced the required qubits by 70.1% on average. Fig. 3(b) shows the number of non-zero elements in the QUBO matrix. While the QUBO matrix for the constraint-based formulation is sparse, it becomes dense in the dictionary-based case. It was observed that the constraint-based formulation outperformed the dictionary-based case in

⁴Note that we have $x_2^2 = x_2$ as each variable is binary, i.e., $0^2 = 0$ and $1^2 = 1$.

Fig. 4. Output probabilities of each GAS iteration for the dictionary-based formulation, where we had $(M, K, Q) = (4, 2, 4)$ and $2^{n_2} = 32$ states.

73.7% of the total IM parameters. The reason why the number of non-zero elements is reduced even though the QUBO matrix of the dictionary-based formulation is dense is because the size of this matrix is different from that of the constraint-based case. For example, the constraint-based QUBO matrix for $(M, K, Q) = (4, 2, 4)$ is 16×16 as given in (21), but the dictionary-based QUBO matrix is 5×5 as given in (32), with different sizes. It can be seen from Fig. 3 that the numbers of required qubits and non-zero elements were in close agreement with the analysis of the derived order. The order depends only on Q and M in the constraint-based case, while the order mainly depends on Q' in the dictionary-based case. Based on these analytical and numerical results, only the dictionary-based formulation is considered in the following comparisons.

B. Optimization process with GAS

Second, as an example of the optimization process, Fig. 4 shows the output probabilities of each trial of GAS. In Fig. 4, the dictionary-based formulation having the IM parameters $(M, K, Q) = (4, 2, 4)$ was considered. A specific definition of the objective function $E_2(\mathbf{x}')$ is given in (31). The horizontal axis of Fig. 4 corresponds to $n_2 = Q' - 1 = 5$ qubits, denoted by $\mathbf{x}' = [x_2 \ x_3 \ x_4 \ x_5 \ x_6]$, where we have $2^{n_2} = 32$ states. As shown in Fig. 4, two best solutions 13 and 19 were successfully marked by GAS. Specifically, the state ID $(13)_{10} = (0 \ 1 \ 1 \ 0 \ 1)_2$ corresponds to $\mathbf{x}' = [0 \ 1 \ 1 \ 0 \ 1]$, which indicates we should use $Q = 4$ patterns: $[1 \ 1 \ 0 \ 0]$, $[1 \ 0 \ 0 \ 1]$, $[0 \ 1 \ 1 \ 0]$, $[0 \ 0 \ 1 \ 1]$ extracted from (8). Additionally, the state ID $(19)_{10} = (1 \ 0 \ 0 \ 1 \ 1)_2$ corresponds to the four patterns of $[1 \ 1 \ 0 \ 0]$, $[1 \ 0 \ 1 \ 0]$, $[0 \ 1 \ 0 \ 1]$, $[0 \ 0 \ 1 \ 1]$. Both can achieve the best performance in terms of BER and AMI owing to $E_2([0 \ 1 \ 1 \ 0 \ 1]) = E_2([1 \ 0 \ 0 \ 1 \ 1]) = 0$, which are optimal. These observations indicated that the quantum circuit for GAS could properly process the proposed objective function and label the target states.

Following Fig. 4, Fig. 5 shows the average of the objective function $E_2(\mathbf{x}')$ corresponding to each iteration of the

Fig. 5. The average of the objective function $E_2(\mathbf{x}')$ of (31) over each iteration.

exhaustive search and GAS. As with Fig. 4, the IM parameters $(M, K, Q) = (4, 2, 4)$ were considered. In this setup, the number of qubits was $n_2 + m_2 = 5 + \lceil \max(E_2(\mathbf{x}')) \rceil + 1 = 5 + 4 + 1 = 10$. It was shown in Fig. 5 that the exhaustive search required $2^{n_2} = 32$ trials in the worst case, while GAS had succeeded in reducing the number of trials dramatically. The proposed formulation was able to provide the quantum speedup for the index selection problem. This is because GAS adaptively changes y , and the quantum circuit can sample the states where $E_2(\mathbf{x}) - y < 0$. However, more trials were required than the theoretical value of $\lceil \pi/4\sqrt{2^5/2} \rceil = 3$, which was caused by the noise in the quantum circuit.

In Figs. 4 and 5, the index selection problem for the case $(M, K, Q) = (4, 2, 4)$ was solved by GAS as a specific example. Ideally, it is better to solve the index selection problem having a large search space, such as $(M, K, Q) = (16, 8, 64)$. However, a quantum circuit with the number of qubits $n_2 + m_2$ can be represented as a unitary matrix of size $2^{n_2+m_2} \times 2^{n_2+m_2}$, which means that the ideal simulation becomes exponentially more complex. It is expected that quantum computers with many more qubits will appear in the near future. When such actual hardware appears, the proposed dictionary-based formulation can be used to solve the previously unsolvable index selection problem having a large search space.

C. Achievable performance comparisons

Finally, it is investigated how much the proposed quantum-assisted method can improve the performance of communication. Since the solution of equiprobable design [6] becomes the same as that of proposed quantum-assisted design in the $(M, K, Q) = (4, 2, 4)$ case of Figs. 4 and 5, instead, the $(M, K, Q) = (6, 3, 4)$ with $L = 1$ was considered as the simplest setup. In the case of $(M, K, Q) = (6, 3, 4)$, the QUBO matrix $\mathbf{M}$ for the constraint-based formulation is given by (33), which is a 24×24 matrix containing 120 non-zero

method improved it to about 3.8. Since the minimum Hamming distance doubled, the diversity order almost doubled accordingly. Hence, the proposed approach was capable of achieving the best BER performance in Fig. 6(a).

Similarly, the improvement in AMI was also observed in Fig. 6(b). As demonstrated in the information-theoretic analysis of IM [2, 42], the equal use of each element such as antennas and subcarriers leads to the improvement of mutual information, and in this figure, the improvement was about 2 [dB]. Since an increase in the minimum Hamming distance increases the minimum Euclidean distance, the proposed method achieved the best AMI with a 1.5 [dB] improvement over the equiprobable design method [6].

VI. CONCLUSIONS

In this paper, the NP-hard index selection problem, which determines the achievable performance of IM, was newly solved by the quantum algorithm GAS. The novel constraint- and dictionary-based formulations were proposed for the problem. For both formulations, the numbers of required qubits and non-zero elements in QUBO matrices were analyzed algebraically, and found to be in close agreement with the actual measurement. The numerical analysis demonstrated that the dictionary-based formulation was capable of reducing the required qubits and was able to provide the quantum speedup as expected in theory. This result implies that future fault-tolerant, large-scale quantum computers may be useful for finding high-performance index activation patterns.

ACKNOWLEDGEMENT

IBM and Qiskit are trademarks of International Business Machines Corporation. The author is indebted to the Editor and the anonymous reviewers for their invaluable suggestions and comments, which further improved this paper.

REFERENCES

- [1] R. Y. Mesleh, H. Haas, S. Sinanovic, C. Ahn, and S. Yun, "Spatial modulation," *IEEE Transactions on Vehicular Technology*, vol. 57, no. 4, pp. 2228–2241, 2008.
- [2] N. Ishikawa, S. Sugiura, and L. Hanzo, "Subcarrier-index modulation aided OFDM – will it work?" *IEEE Access*, vol. 4, pp. 2580–2593, 2016.
- [3] D. Slepian, "Permutation modulation," *Proceedings of the IEEE*, vol. 53, no. 3, pp. 228–236, 1965.
- [4] N. Ishikawa, S. Sugiura, and L. Hanzo, "50 years of permutation, spatial and index modulation: From classic RF to visible light communications and data storage," *IEEE Communications Surveys & Tutorials*, vol. 20, no. 3, pp. 1905–1938, 2018.
- [5] P. K. Frenger and N. A. B. Svensson, "Parallel combinatory OFDM signaling," *IEEE Transactions on Communications*, vol. 47, no. 4, pp. 558–567, 1999.
- [6] M. Wen, Y. Zhang, J. Li, E. Basar, and F. Chen, "Equiprobable subcarrier activation method for OFDM with index modulation," *IEEE Communications Letters*, vol. 20, no. 12, pp. 2386–2389, 2016.
- [7] S. Dang, G. Chen, and J. P. Coon, "Lexicographic codebook design for OFDM with index modulation," *IEEE Transactions on Wireless Communications*, vol. 17, no. 12, pp. 8373–8387, 2018.
- [8] N. Ishikawa, "IMToolkit: An open-source index modulation toolkit for reproducible research based on massively parallel algorithms," *IEEE Access*, vol. 7, pp. 93 830–93 846, 2019.
- [9] Y. Shi, X. Lu, K. Gao, J. Zhu, and S. Wang, "Genetic algorithm aided OFDM with all index modulation," *IEEE Communications Letters*, vol. 23, no. 12, pp. 2192–2195, 2019.
- [10] A. Fazeli and H. H. Nguyen, "Code design for non-coherent index modulation," *IEEE Communications Letters*, vol. 24, no. 3, pp. 477–481, 2020.
- [11] R. Y. Chang, S. J. Lin, and W. H. Chung, "New space shift keying modulation with Hamming code-aided constellation design," *IEEE Wireless Communications Letters*, vol. 1, no. 1, pp. 2–5, 2012.
- [12] —, "A method for the construction of hierarchical generalized space shift keying (GSSK) modulation for unequal error protection," *Physical Communication*, vol. 9, pp. 88–96, 2013.
- [13] R. P. Feynman, "Quantum mechanical computers," *Foundations of Physics*, vol. 16, no. 6, pp. 507–531, 1986.
- [14] P. Shor, "Algorithms for quantum computation: Discrete logarithms and factoring," in *Annual Symposium on Foundations of Computer Science*, Santa Fe, NM, USA, Nov. 20–22, 1994.
- [15] L. K. Grover, "A fast quantum mechanical algorithm for database search," in *ACM Symposium on Theory of Computing*, Philadelphia, Pennsylvania, USA, May 22–24, 1996.
- [16] K. Fujii, "Noise threshold of quantum supremacy," *arXiv:1610.03632 [quant-ph]*, 2016.
- [17] K. Fukui, A. Tomita, A. Okamoto, and K. Fujii, "High-threshold fault-tolerant quantum computation with analog quantum error correction," *Physical Review X*, vol. 8, no. 2, p. 021054, 2018.
- [18] M. Amico, Z. H. Saleem, and M. Kumph, "Experimental study of Shor's factoring algorithm using the IBM Q Experience," *Physical Review A*, vol. 100, no. 1, p. 012305, 2019.
- [19] C. Durr and P. Hoyer, "A quantum algorithm for finding the minimum," *arXiv:quant-ph/9607014*, 1999.
- [20] D. Bulger, W. P. Baritompa, and G. R. Wood, "Implementing pure adaptive search with Grover's quantum algorithm," *Journal of Optimization Theory and Applications*, vol. 116, no. 3, pp. 517–529, 2003.
- [21] A. Gilliam, M. Pistoia, and C. Gondiulea, "Optimizing quantum search using a generalized version of Grover's algorithm," *arXiv:2005.06468 [quant-ph]*, 2020.
- [22] A. Gilliam, S. Woerner, and C. Gondiulea, "Grover adaptive search for constrained polynomial binary optimization," *Quantum*, vol. 5, 2021.
- [23] —, "Grover adaptive search for constrained polynomial binary optimization," *arXiv:1912.04088 [quant-ph]*, 2020.
- [24] A. Peruzzo, J. McClean, P. Shadbolt, M. H. Yung, X. Q. Zhou, P. J. Love, A. Aspuru-Guzik, and J. L. O'Brien, "A variational eigenvalue solver on a photonic quantum processor," *Nature Communications*, vol. 5, no. 1, 2014.
- [25] E. Farhi, J. Goldstone, and S. Gutmann, "A quantum approximate optimization algorithm," *arXiv:1411.4028*, 2014.
- [26] S. Harwood, C. Gambella, D. Trenev, A. Simonetto, D. Bernal, and D. Greenberg, "Formulating and solving routing problems on quantum computers," *IEEE Transactions on Quantum Engineering*, vol. 2, pp. 1–17, 2021.
- [27] B. Apolloni, C. Carvalho, and D. de Falco, "Quantum stochastic optimization," *Stochastic Processes and their Applications*, vol. 33, no. 2, pp. 233–244, 1989.
- [28] T. Kadowaki and H. Nishimori, "Quantum annealing in the transverse Ising model," *Physical Review E*, vol. 58, no. 5, pp. 5355–5363, 1998.
- [29] T. Inagaki, Y. Haribara, K. Igarashi *et al.*, "A coherent Ising machine for 2000-node optimization problems," *Science*, vol. 354, no. 6312, pp. 603–606, 2016.
- [30] M. Hasegawa, H. Ito, H. Takesue, and K. Aihara, "Optimization by neural networks in the coherent Ising machine and its application to wireless communication systems," *IEICE Transactions on Communications*, vol. E104.B, no. 3, pp. 210–216, 2020.
- [31] K. Kurasawa, K. Hashimoto, A. Li, K. Sato, K. Inaba, H. Takesue, K. Aihara, and M. Hasegawa, "A high-speed channel assignment algorithm for dense IEEE802.11 systems via coherent Ising machine," *IEEE Wireless Communications Letters*.
- [32] P. Botsinis, S. X. Ng, and L. Hanzo, "Quantum search algorithms, quantum wireless, and a low-complexity maximum likelihood iterative quantum multi-user detector design," *IEEE Access*, vol. 1, pp. 94–122, 2013.
- [33] M. Boyer, G. Brassard, P. Hoyer, and A. Tapp, "Tight bounds on quantum searching," *Fortschritte der Physik*, vol. 46, no. 4–5, pp. 493–505, 1998.
- [34] P. Botsinis, D. Alanis, Z. Babar, S. X. Ng, and L. Hanzo, "Coherent versus non-coherent quantum-assisted solutions in wireless systems," *IEEE Wireless Communications*, vol. 24, no. 6, pp. 144–153, 2017.
- [35] T. Matsumine, T. Koike-Akino, and Y. Wang, "Channel decoding with quantum approximate optimization algorithm," in *IEEE International Symposium on Information Theory*, 2019.
- [36] P. Botsinis, D. Alanis, Z. Babar, H. V. Nguyen, D. Chandra, S. X. Ng,

- and L. Hanzo, "Quantum search algorithms for wireless communications," *IEEE Communications Surveys & Tutorials*, vol. 21, no. 2, pp. 1209–1242, Secondquarter 2019.
- [37] A. Gilliam, C. Venci, S. Muralidharan, V. Dorum, E. May, R. Narasimhan, and C. Gocialea, "Foundational patterns for efficient quantum computing," *arXiv:1907.11513 [quant-ph]*, 2021.
- [38] A. Lucas, "Ising formulations of many NP problems," *Frontiers in Physics*, vol. 2, 2014.
- [39] J. Jeganathan, A. Ghayeb, and L. Szczecinski, "Generalized space shift keying modulation for MIMO channels," in *IEEE International Symposium on Personal, Indoor and Mobile Radio Communications*, Cannes, France, Sept. 15–18, 2008.
- [40] E. Basar, U. Aygolu, E. Panayirci, and H. V. Poor, "Orthogonal frequency division multiplexing with index modulation," *IEEE Transactions on Signal Processing*, vol. 61, no. 22, pp. 5536–5549, 2013.
- [41] G. Aleksandrowicz, T. Alexander, P. Barkoutsos *et al.*, "Qiskit: An open-source framework for quantum computing," *Zenodo*, 2019.
- [42] M. Wen, X. Cheng, M. Ma, B. Jiao, and H. V. Poor, "On the achievable rate of OFDM with index modulation," *IEEE Transactions on Signal Processing*, vol. 64, no. 8, pp. 1919–1932, 2016.

Naoki Ishikawa (S'13–M'17) was born in Kanagawa, Japan, in 1991. He received the B.E., M.E., and Ph.D. degrees from the Tokyo University of Agriculture and Technology, Tokyo, Japan, in 2014, 2015, and 2017, respectively. In 2015, he was an academic visitor with the School of Electronics and Computer Science, University of Southampton, UK. From 2016 to 2017, he was a research fellow of the Japan Society for the Promotion of Science. From 2017 to 2020, he was an assistant professor in the Graduate School of Information Sciences, Hiroshima

City University, Japan. Since 2020, he has been an Associate Professor with the Faculty of Engineering, Yokohama National University, Japan. He was certified as an Exemplary Reviewer of IEEE TRANSACTIONS ON COMMUNICATIONS 2017. He received the Yasujiro Niwa Outstanding Paper Award from Tokyo Denki University in 2018, the Telecom System Technology student Award (honorable mention) from Telecommunications Advancement Foundation of Japan in 2014, and the Outstanding Paper Award for Young C&C Researchers from NEC C&C Foundation in 2014. His research interests include massive MIMO, physical layer security, and quantum speedup for wireless communications.