Tunable, large X-band microwave absorbers using variable chessboard surfaces

This paper was downloaded from TechRxiv (<https://www.techrxiv.org>).

LICENSE

CC BY-NC-SA 4.0

SUBMISSION DATE / POSTED DATE

02-12-2021 / 10-12-2021

CITATION

Ruiz Perez, Fernando; Estrada, Santos Martín López; Caballero-Briones, Felipe (2021): Tunable, large X-band microwave absorbers using variable chessboard surfaces. TechRxiv. Preprint.
<https://doi.org/10.36227/techrxiv.17109152.v1>

DOI

[10.36227/techrxiv.17109152.v1](https://doi.org/10.36227/techrxiv.17109152.v1)

Tunable, large X-band microwave absorbers using variable chessboard surfaces

F. Ruiz-Perez, S. M. López-Estrada, F. Caballero-Briones

Abstract

In this communication, the design and electromagnetic absorption of a metamaterial coating with a broad modifiable absorption in the 8 to 12 GHz frequency range, corresponding to the X-band, is reported. The unit of the coating material consists of a chessboard with chess squares of different heights made of a rGO/Fe₃O₄/PPy composite. The influence of the height ratio of the chess squares in a 5 x 5 chessboard on the attenuation response of electromagnetic radiation in the X band was studied *in silico*. The results demonstrate that the chessboard-like microwave absorber exhibit tunable response, with a maximum effective attenuation of -37.43 dB/GHz in the X band range, ca. 24 % higher than the best single layer coating.

Index Terms: Chessboard, composite, X-band, microwave absorber.

Take-Home Messages:

- In silico study of chessboard structure of rGO/Fe₃O₄/PPy as microwave absorber.
- The chessboard structure showed a tunable attenuation response in X-band region.
- Maximum reflection loss of -35.83 dB and an effective attenuation in the X-band of -37.45 dB/GHz was achieved.

Introduction

With the constant development of radar (Radio Detection and Ranging) systems, the investigation focusing on radar absorbing materials (RAM's) attracts increasing attention. Electromagnetic absorbers are a type of materials that absorb the incident electromagnetic

Submission date: November 8th, 2021

The authors have no conflicts to disclose. This work was supported by SIP-IPN 20211513. F. Ruiz Perez is financed by CONACyT PhD and by BEIFI-IPN grants.

F. Ruiz-Perez and F. Caballero Briones are with the Instituto Politécnico Nacional, Materiales y Tecnologías para Energía, Salud y Medio Ambiente (GESMAT), CICATA Altamira. 89600, Altamira, México.

S. M. López Estrada is with the Unidad de Investigación y Desarrollo Tecnológico (UNINDETEC), SEMAR, 96269, Antón Lizardo, México.

Corresponding author: F. Caballero-Briones, e-mail: fcaballero@ipn.mx

waves, attenuating the outgoing waves. These materials have important applications in areas such as invisibility cloaks, camouflage, stealth technology and electromagnetic shielding [1,2]. The development of RAM's for the X-band (8-12 GHz) is of particular interest for civilian and military applications, for example, to ensure that tracking systems cannot detect targets in the area, prevent aerial interception. However, despite the large absorption peaks achieved in the literature, most of the studied metamaterials show a narrow absorption bandwidth, therefore, many efforts have been made to extend the bandwidth and cover wider bands of the electromagnetic spectrum [3–5]. For example, a 3 mm coating of a composite made of reduced graphene oxide (rGO), magnetite (Fe_3O_4) and polypyrrole (PPy) has a reported maximum absorption of -49.2 dB at 11.8 GHz, with a maximum effective absorption *i.e.*, attenuation above -10 dB in the studied band, of -28.76 dB/GHz [6]. Some strategies to increase the bandwidth are the use of multilayer materials [7,8], although they could suffer delamination due to interfacial stress during wearing. Other strategies include the use of metamaterials such as Au metallic metasurface arrays [9], chessboard-like metasurfaces with either alternating tiles [10] or square annular magnetic conductors, and Jerusalem cross structures [11]. However, the use of single layer, graphene-based absorbers in a metamaterial configuration have not been reported as wide band absorbers, to the best of our knowledge

In this letter, we report an *in-silico* study of the microwave attenuation response of a chessboard structure formed by squares of different heights made of the rGO/ Fe_3O_4 /PPy composite, optimizing the height ratio to maximize the effective absorption in the X-band.

Materials and Methods

In the present study, the rGO/ Fe_3O_4 /PPy composite reported by Zhang *et al.* [6] was used as coating material. The PPy and the addition of Fe_3O_4 adjust the permittivity and improve the impedance matching between the dielectric and the magnetic losses which allows the EM wave to penetrate the material and its subsequent dissipation as thermal energy. For the simulation reported here, Fig. 1a) shows a 5x5 chessboard-like surface composed by squares

with two different heights which were varied as shown in the 1. The simulation process was carried out using CST Studio software. The simulation parameters were set to obtain the reflectivity values in dB for varying the cells height in the frequency range 2-18 GHz [12]. The boundary conditions, material structure, and port configuration for the simulated measurement are shown in Fig. 1b). The simulated structure is composed of a perfect electric conductor (PEC) sheet as substrate, and as absorber, a single layer of the rGO/Fe₃O₄/PPy composite reported in [11].

Fig. 1. a) Chessboard structure rGO/Fe₃O₄/PPy composite. b) Setup used for simulation of proposed structure in CST studio.

Table 1. Height setup of the chess squares.

H (mm)	h (mm)	h/H
5	4	0.8
5	2.8	0.56
5	2.7	0.54
5	2.5	0.5
5	2.4	0.48
5	2	0.4
4	2.8	0.7
4	2.7	0.675
4	2.6	0.65
4	2.5	0.625
4	2.1	0.525

Results and Discussion

Figure 2 presents the simulated attenuation response of the designed metamaterials in the 2-18 GHz range. Figure 2a) presents single-layer, single thickness materials where the reported maximum absorption of -37 dB at 11.8 GHz for the optimized rGO/Fe₃O₄/PPy coating [11] is clearly observed. Despite the large absorption, the peak width is quite narrow. For comparison, in Figure 2b) the attenuation response of the designed metamaterials is presented. It can be observed that the maximum attenuation peak can be thoroughly modulated in the X-band, as well as the area under the curve.

Fig 2. Attenuation responses of a) single layer, rGO/Fe₃O₄/PPy composite with varying thickness; b) chessboard metamaterials with varying height ratios.

Figure 3 presents the effective attenuation in the X-band, defined as the area under the curve where the reflection loss is higher than -10 dB within the 8-12 GHz range as shown in Figure 3a) inset. Figure 3a) presents the effective attenuation values of the single layer coatings. The effective attenuation reaches a maximum of -28.77 dB/GHz corresponding to a layer of 3 mm; for layers with higher or lower thickness, the effective attenuation reduces abruptly. Figure 3b) presents the effective attenuation of the metamaterials based in chessboards constructed with H being 4 mm or 5 mm at the different h/H ratios. The effective attenuation increases with the height ratio, *i.e.*, as the difference between the highest (H) and the shortest

(h) square decreases. Limit effective attenuations were reached with h/H ratios of 0.53 and 0.66 for $H = 4$ mm and $H = 5$ mm, respectively. The chessboard configuration with $h=2.7$ mm and $H=4$ mm has the largest effective attenuation with -37.45 dB/GHz within the X-band, which corresponds to an increase of the total incident wave absorption of ca. 24% for the optimized chessboard configuration. After this *in silico* study, the preparation and experimental attenuation testing of the proposed coatings is intended.

Fig 3. Effective attenuation in the X-band (8-12 GHz) of a) Single layer coating. b) Chessboard coating.

Conclusions

A single-layer chessboard structure with tunable absorption and large effective attenuation in the radar X-band, was investigated *in silico*. The simulated 5×5 chessboard was built by fixing the height of the “white” squares and varying the height of the “black” squares to study the effect of the height ratio on the effective attenuation of the structure in the 8-12 GHz range. The squares were made of a $rGO/Fe_3O_4/PANI$ composite. The results showed a maximum attenuation value of -35.83 dB at 10 GHz with a height configuration of $H=4$ mm and $h=2.7$ mm, with an effective bandwidth absorption, *i.e.*, above -10 dB in the X-band range, of -37.45 dB/GHz. In contrast with the response of single layer coatings, the chessboard structure allowed to modulate the attenuation frequency throughout the region of

interest, as well as obtaining a wide band width. This study provides a first approach to further characterizations of the proposed structures in a real operative environment.

CRedit author statement

F. Ruiz-Perez: Conceptualization, Software, Investigation, Methodology, Validation, Visualization, Writing – Original Draft. **S. M. López Estrada:** Conceptualization, Supervision, Writing – Original Draft. **F. Caballero-Briones:** Conceptualization, Supervision, Formal analysis, Visualization, Writing – Original Draft.

References

- [1] Islam SS, Hasan MM, Faruque MRI. A new metamaterial-based wideband rectangular invisibility cloak. *Appl Phys A* [Internet]. 2018;124:160. Available from: <http://link.springer.com/10.1007/s00339-018-1590-9>.
- [2] Magisetty R, Raj AB, Datar S, et al. Nanocomposite engineered carbon fabric-mat as a passive metamaterial for stealth application. *J Alloys Compd* [Internet]. 2020;848:155771. Available from: <https://linkinghub.elsevier.com/retrieve/pii/S0925838820321356>.
- [3] Handoko E, Budi S, Sugihartono I, et al. Microwave absorbing properties of teflon coating for x-band frequencies. 2021. p. 030002. Available from: <http://aip.scitation.org/doi/abs/10.1063/5.0037747>.
- [4] Di X, Wang Y, Fu Y, et al. Wheat flour-derived nanoporous carbon@ZnFe₂O₄ hierarchical composite as an outstanding microwave absorber. *Carbon N Y* [Internet]. 2021;173:174–184. Available from: <https://linkinghub.elsevier.com/retrieve/pii/S0008622320310745>.
- [5] Zhang X, Liu Z, Deng B, et al. Honeycomb-like NiCo₂O₄@MnO₂ nanosheets array/3D porous expanded graphite hybrids for high-performance microwave absorber with hydrophobic and flame-retardant functions. *Chem Eng J* [Internet]. 2021;419:129547. Available from: <https://linkinghub.elsevier.com/retrieve/pii/S1385894721011347>.

- [6] Zhang C, Chen Y, Li H, et al. Facile Fabrication of Three-Dimensional Lightweight RGO/PPy Nanotube/Fe₃O₄ Aerogel with Excellent Electromagnetic Wave Absorption Properties. ACS Omega [Internet]. 2018;3:5735–5743. Available from: <https://pubs.acs.org/doi/10.1021/acsomega.8b00414>.
- [7] Liu T, Kim S-S. Ultrawide Bandwidth Electromagnetic Wave Absorbers Using a High-capacitive Folded Spiral Frequency Selective Surface in a Multilayer Structure. Sci Rep [Internet]. 2019;9:16494. Available from: <http://www.nature.com/articles/s41598-019-52967-z>.
- [8] Liu T, Kim S-S. Ultrawide Bandwidth Electromagnetic Wave Absorbers Composed of Double-Layer Frequency Selective Surfaces with Different Patterns. Sci Rep [Internet]. 2018;8:13889. Available from: <http://www.nature.com/articles/s41598-018-32181-z>.
- [9] Feng X, Xie X, Pu M, et al. Hierarchical metamaterials for laser-infrared-microwave compatible camouflage. Opt Express [Internet]. 2020;28:9445. Available from: <https://www.osapublishing.org/abstract.cfm?URI=oe-28-7-9445>.
- [10] Haji-Ahmadi M-J, Nayyeri V, Soleimani M, et al. Pixelated Checkerboard Metasurface for Ultra-Wideband Radar Cross Section Reduction. Sci Rep [Internet]. 2017;7:11437. Available from: <http://www.nature.com/articles/s41598-017-11714-y>.
- [11] Chen H, Shen R, Li F, et al. Design of phase matching chessboard-like electromagnetic metasurfaces for wideband radar cross section reduction. Microw Opt Technol Lett [Internet]. 2019;61:2037–2045. Available from: <https://onlinelibrary.wiley.com/doi/10.1002/mop.31854>.
- [12] Lee YS, Wee FH, You KY, et al. Study of single layer microwave absorber based on rice husk Ash/CNTs composites. Indones J Electr Eng Comput Sci [Internet]. 2019;14:929. Available from: <http://ijeecs.iaescore.com/index.php/IJEECS/article/view/16812>.